



## Dimensions

### CD3000E-3PH 25-75A

	W	H	D
25A	116	316	187
35A	116	316	187
45A	116	316	187
75A	116	316	187

### CD3000E-3PH 100-225A

	W	H	D
100A	137	440	270
125A	137	440	270
150A	137	440	270
225A	262	440	270

### CD3000E-3PH 300-400A

	W	H	D
300A	262	520	270
350A	262	520	270
400A	262	520	270

### CD3000E-3PH 450-500A

	W	H	D
450A	262	520	270
500A	262	520	270

## Fuses and Fuseholder

Internal Fuses are standard on CD3000E-3PH.

## Input features

Input signal	Input impedance
0-10V	8200 $\Omega$
4-20mA	100 $\Omega$
10K $\Omega$ Potentiometer	8200 $\Omega$

Auxiliary Power Supply : 90-240Vac

## Output features

Current	Voltage range (V)	Repetitive peak reverse voltage (480V)	Latching current (mAeff)	Max peak one cycle (10msec.) (A)	Leakage current (mAeff)	I <sup>2</sup> T value for fusing tp=10msec	Frequency range (V)	Power loss I=Inom (W)	Isolation voltage (Vac)
25A	330→480 V	1200	450	500	15	1030	47→70	90	2500
35A	330→480 V	1200	450	1000	15	4750	47→70	126	2500
45A	330→480 V	1200	450	1000	15	4810	47→70	162	2500
75A	330→480 V	1200	450	1000	15	4810	47→70	270	2500
100A	330→480 V	1200	450	1540	15	11300	47→70	360	2500
125A	330→480 V	1200	450	2000	15	19100	47→70	450	2500
150A	330→480 V	1200	450	2000	15	19100	47→70	540	2500
225A	330→480 V	1200	300	4800	15	108000	47→70	810	2500
300A	330→480 V	1200	300	5250	15	128000	47→70	1080	2500
350A	330→480 V	1200	200	7800	15	300000	47→70	1260	2500
400A	330→480 V	1200	200	8000	15	306000	47→70	1440	2500
450A	330→480 V	1200	1000	17800	15	1027000	47→70	1620	2500
500A	330→480 V	1200	1000	17800	15	1027000	47→70	1800	2500

## Warranty / Remedy

Honeywell warrants goods of its manufacture as being free of defective materials and faulty workmanship. Contact your local sales office for warranty information. If warranted goods are returned to Honeywell during the period of coverage, Honeywell will repair or replace without charge those items it finds defective. The foregoing is Buyer's sole remedy and is in lieu of all other warranties, expressed or implied, including those of merchantability and fitness for a particular purpose. Specifications may change without notice. The information we supply is believed to be accurate and reliable as of this printing. However, we assume no responsibility for its use. While we provide application assistance personally, through our literature and the Honeywell web site, it is up to the customer to determine the suitability of the product in the application.

Distributor :

**Insteng Process Automation Ltd**  
 Unit 3, Moy Road Industrial Estate  
 Taffs Well  
 Cardiff  
 CF15 7QR  
 Phone: 029 2081 5000  
 Fax: 029 2081 3051  
 e-mail: sales@insteng.co.uk  
 www.insteng.co.uk